



FEATURES

- 200 + 200 Watt / 350 + 350 Watt zone PA Amplifier
- 2-zone amplifier with each zone having its independent tone and master controls for separate and combined operation.
- Individual zone ON/OFF Facility for output to maintain desire level and zones can be ON/OFF without disturbing volume settings.
- Line input and output on each zone.

- 2 zone music operations For DJ and Live programs
- Two separate groups of speakers simultaneously can be operated on Mono mode ideal for Places of Worship
- Built in FM, MP3 Player Through USB, SD & MMC card reader with remote control
- AC & 36V DC Operation





MODEL NO	CTZ 4000U	CTZ 7000U
Power Supply	AC: 220-240, 50/60Hz DC: 36V Car Battery	AC: 220-240, 50/60Hz DC : 36V Car Battery
Power Output	200W + 200W, 10% THD at 300W RMS Max. Each Zone	350W + 350W, 10% THD at 400W RMS Max. Each Zone
Input Channels	Stereo input 200mV/100k Ω Line input 1V/50k Ω 6xMic.1mV/4.7k Ω 2x Aux. 100mV/470k Ω	Stereo input 200mV/100k Ω , Line input 1 V/50k Ω , 6xMic.1mV/4.7k Ω 2x Aux. 100mV/470k Ω
Frequency Response	50-15000 Hz ±3 dB For Each Zone	50-1500OHz ± 3dB for Each Zone
Tone Control	Bass: (100Hz) ±10dB Treble: (10 kHz) ±10dB	Bass: (100Hz) ±10dB , Treble: (10 kHz) ±10dB
Digital Player	FM , Mp3 Player, Through USB, SD & MMC CARD READER WITH REMOTE CONTROI	FM , Mp3 Player Through USB, SD & MMC CARD READER WITH REMOTE CONTROL
Speaker Output	4Ω , 8Ω , 70 V & 100 V for Each Zone	4Ω , 8Ω , 70 V & 100V for Each Zone

Office: B1+B2+B3/I, Gandhinagar Electronic Zone Industrial Estate, GIDC, Sector -25, Gandhinagar (380 006), Gujarat, India. Ph: +91 79 40407000