



FEATURES

CKA 1000U

- 100 Watt PA Amplifier
- 5 Mic and 2 Aux. Inputs
- Built in FM, MP3 Player Through USB, SD & MMC card reader with remote control
- 100V line inputs for connecting another amplifier's output in long line application
- AC & 12V DC Operation
- Bass & Treble tone controls cut type.

CKA 1600U

- 160 Watt PA Amplifier
- 6 Mic and 2 Aux. Inputs
- Built in FM, MP3 Player Through USB, SD & MMC card reader with remote control
- 100V line inputs for connecting another amplifier's output in long line application
- AC & 24V DC Operation
- Bass & Treble tone controls cut type.



MODEL NO	CKA 1000U	CKA-1600U
Power Supply	AC: 220-240, 50/60Hz DC: 12V Car Battery	AC: 220-240, 50/60Hz DC: 24V Car Battery
Power Output	100W RMS, 10% THD at 130W RMS Max	160W RMS, 10% THD at 175W RMS Max
Input Channels	5 x Mic. 1mV/4.7kΩ 2xAux.100mV/100kΩ	6 x Mic. 1mV/4.7kΩ 2xAux.70mV/100kΩ
Frequency Response	50-15000 HZ±2dB	50-15000 HZ±2dB
Tone Control	Bass: (100Hz) ±10dB Treble: (10 kHz) ±10dB	Bass: (100Hz) ±10dB Treble: (10 kHz) ±10dB
Digital Player	FM, Mp3 Player, Through USB, SD & MNIC CARD READER WITH REMOTE CONTROL	FM, Mp3 Player, Through USB, SD & MMC. CARD READER WITH REMOTE CONTROL
Speaker Output	4Ω, 8Ω, 16Ω & 100V Line	4Ω, 8Ω, 16Ω, 70V, 100V Line